



## Model 542X-Series Dante® Intercom Audio Engine Feature-by-Feature Comparison Chart

	Model 5421 / Model 5421A	Model 5422A-01	Model 5422A-02
Number of Dante Channels	16	32	64
Number of Dante Flows (each direction)	16 / 32	32	32
Maximum Number of Groups	4	8	16
Party-Line (PL) Mode w/Auto Mix	•	•	•
Summing Bus Mode w/Auto Mix	•	•	•
IFB Modes (VOX/TOX)		•	•
Audio Switching Modes		•	•
Pass-Thru Mode	•	•	•
Custom Group Names		•	•
Custom Dante Channel Names		•	•
Configured using STcontroller	•		
Discoverable using STcontroller		•	•
Configured using Web Browser		•	•
GigE Ethernet Ports	1	3	3
Redundant Dante		•	•
Independent Management Port		•	•
PoE Powering	•		
AC Mains Powering		•	•
DC Powering		•	•
Firmware Updating	USB	USB	USB
Enclosure	1/2 Rack (optional 1 RU)	1 RU	1 RU